

NASA TECH BRIEF




NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Division, NASA, Code UT, Washington, D.C. 20546.

Low-Power Integrated-Circuit Driver for Ferrite-Memory Word Lines

The problem:

Standard bidirectional current drivers utilize *nnp* bipolar transistors and transformers. These circuits possess negligible quiescent power dissipation. Also, the transformers complicate integrated-circuit (IC) fabrication of these schemes. Circuits using only *nnp*



Schematic of BIMOS Word-Drive Circuit

bipolar transistors consume excessive power. Although complementary bipolar circuits can provide bidirectional word-drive current pulses, fabricating high-quality *nnp* and *npn* devices on a common substrate also presents problems.

The solution:

A newly developed word-line drive circuit, realizable in IC form, generates bidirectional current pulses and consumes little power. Also, current-pulse amplitudes and rise times are independent of active-device parameters. This composite circuit uses both *nnp* bipolar and *p*-channel MOS transistors (BIMOS).

How it's done:

The figure shows the new BIMOS word-driver circuit. Each driver uses three bipolar *nnp* transistors (Q1, Q2, and Q3), one MOS *p*-channel device (Q4), and three internal resistors (R1, R2, and R3). Inputs consist of a positive supply line (V_S), a write line (V_W), a read line (V_R), and a write current line (V_{IN}). The emitter of Q3 and the collector of Q2 provide an output (V_O) which drives a single laminated-ferrite word line. Two external precision resistors, R_R and R_W , set the amplitude and rise time, respectively, of the read and write current pulses.

The BIMOS driver provides (1) ease of IC construction; (2) low standby power consumption; (3) bidirectional current pulses; and (4) current-pulse amplitudes and rise times independent of active-device parameters, e.g., transistor beta.

Note:

Requests for further information may be directed to:

Technology Utilization Officer
Headquarters
National Aeronautics
and Space Administration
Washington, D.C. 20546
Reference: TSP70-10374

Patent status:

This invention is owned by NASA, and a patent application has been filed. Royalty-free, nonexclusive licenses for its commercial use will be granted by NASA. Inquiries concerning license rights should be made to NASA, Code GP, Washington, D.C. 20546.

Source: S. Katz of
RCA Corporation
under contract to
Electronics Research Center
(ERC-10212)
Category 09